

010846

The PoE VoIP Paging Gateway enables access to existing paging speakers through a VoIP phone system. This gateway uses a standard paging amplifier and supports paging to multiple zones from a VoIP phone.

Product Specifications	
Regulatory Compliance	FCC Class A, UL 60950, CE
Power Requirement	PoE or +48VDC
Baud Rate	10/100 Mbps
Protocol	SiP compliant
Part Number	010846
Dimensions	6.11"L x 4.05"W x 1.15" H
Weight	1.2 lbs.




Getting started

- Be sure that you have received all the parts described in "Parts list."
- Download the *VoIP Paging Gateway Operations Guide* PDF file from the PoE VoIP Paging Gateway product page, at: <http://www.cyberdata.net/products/voip/legacyanalog/paginggateway/docs.html>


Parts list

(1) VoIP Paging Gateway	(1) Mounting Template (see the last page)
(1) Mounting Kit	
(2) #6 Mounting Anchors	(2) #6 x 1 1/2" Screws

Typical paging system setup using the Paging Gateway



Mounting (optional) and setting up the PoE VoIP Paging Gateway



Verifying operations and settings

Front View with LEDs

- Green **Link** light indicates network connectivity
- Orange **Link** light indicates 100Mbps baud rate
- Yellow **Link** light indicates 10Mbps baud rate
- Blinking yellow **Act** light indicates network activity
- Blinking blue **Status** light indicates the unit is running
- Green **Paging** light indicates the unit is paging

Back View with Test/ Reset Switch

To announce the Paging Gateway's current IP address, press the end of a paper clip into the **Test/Reset** switch on the back of the unit. When the unit beeps after pressing the switch for one second, release the switch to hear the IP address announcement.

To restore the Paging Gateway's factory default settings, press and hold the **Test/Reset** switch while all the indicator lights turn off. Continue to press the switch until after the indicator lights turn back on, and then release the switch. All Paging Gateway settings are restored to the factory defaults, the unit announces its restored default IP address, and then announces that it is rebooting.

Contacting CyberData

Corporate Headquarters

CyberData Corporation
3 Justin Court
Monterey, CA 93940, USA

Phone: 831-373-2601
Fax: 831-373-4193
www.CyberData.net

Sales: (831) 373-2601 ext. 334

Support: 831-373-2601 ext. 333
Web: <http://www.cyberdata.net/support/contactsupportvoip.html>

RMA Dept: (831) 373-2601 ext. 136
Email: RMA@CyberData.net
RMA Status: <http://www.cyberdata.net/support/rmastatus.html>

Warranty

CyberData warrants its product against defects in material or workmanship for a period of two years from the date of purchase. Should the product fail within the warranty period, CyberData will repair or replace the product free of charge. This warranty includes all parts and labor.

Should the product fail out-of-warranty, a flat rate repair charge of one half of the purchase price of the product will be assessed. Repairs that are in warranty but are damaged by improper modifications or abuse, will be charged at the out-of-warranty rate. Products shipped to CyberData, both in and out-of-warranty, are shipped at the expense of the customer. Shipping charges for repaired products shipped back to the customer by CyberData, will be paid by CyberData.

CyberData shall not under any circumstances be liable to any person for any special, incidental, indirect or consequential damages, including without limitation, damages resulting from use or malfunction of the products, loss of profits or revenues or costs of replacement goods, even if CyberData is informed in advance of the possibility of such damages.

For product service, contact the Returned Materials Authorization (RMA) department. A product will not be accepted for return without an approved RMA number. Send the product, in its original package, to: CyberData Corporation, 2555 Garden Road, Monterey, CA 93940, Attention: RMA "your RMA number"

The most recent warranty information is available at:
Web: <http://www.cyberdata.net/support/warranty/index.html>